

SK1 USA STANDARD SETUP 14 May 2013 READ ME

The SK1 USA STANDARD SETUP replaces the first 10 [User] Patches with Patches created by Hammond USA in conjunction with our Top Artists. These Patches represent the most requested and popular foundation sounds of the Keyboard world. The [User] Leslie Cabinets have been “Tweaked” as well.

You can use these patches as “base” patches, tailoring them to suit your taste and requirement, then copying them to other [User] locations.

If you have not done so, please make sure you have updated your SK to the latest release of the SK System Software.

Please return to www.hammondorganco.com to get the latest update. Follow the instructions on our website to complete the update.


After making sure your SK has the latest System Software, copy the new SK1 USA STANDARD setup file from your computer into the “SETUPS” folder on the USB “Jump” drive you have established for your SK.

It is not recommended you copy this “Read Me” file onto your “Jump” drive. If you have not established a “Jump” drive for your SK, please refer to your SK owners guide for instructions in how to do so.

Eject the “jump” drive from your computer and attach it to your SK’s USB port. Wait for your SK to recognize the drive.

IMPORTANT: Installing this setup will ERASE all the settings you have stored on your SK in favor of the ones contained in this setup. If you have made changes to your stored settings, you will want to back up your current setup before you install this new one.


TO SAVE YOUR CURRENT SETUP



Press the [MENU/EXIT] button, and use the [▲] Cursor Buttons to arrive at the “D” Menu Screen. Use the [▶] Cursor Button to tab over to “SETUP”. Press [ENTER].

If you have not saved your setup as of yet the screen will say “NEW FILE” [ENT] to Save. Make sure that the “SU” Designation is at the right side of the screen, if it says “WH”, use the [▶] cursor button to select the screen and use the [VALUE] knob to change “Whole” to “Setup”. Use the [◀] cursor button to return to the save screen. If you have already done some “saving”, spin the [VALUE] knob until you get to the “NEW FILE” screen. Now press [ENTER] to save your setup.

TO INSTALL THE USA STANDARD SETUP



Spin the VALUE dial until the “SK1 STD” file appears. Press [ENTER]. It will only take a few second to load. Remove your USB drive and press [PLAY].

The 10 favorites will correspond to the 10 new presets.

Here are brief descriptions of the ten new presets:

1. VINTAGE B-3

This is modeled after a road-worn Vintage Hammond B-3 and 147 Leslie with maximum leakage, tube amp overdrive, aged Chorus-Vibrato, and heightened key-click.

2. CRUNCH B-3

This is an overdriven Vintage Hammond B-3 with 3300-style Tube Overdrive Leslie.

3. FULL ORGAN

This is a Clean Vintage Hammond B-3 with 122 Style Leslie.

4. FARF COMBO ORGAN

This is a “Full Organ” setting of the Popular Italian Combo Organ of the 1960’s.

5. Vx with Rho Bass

This patch recalls the on-stage keyboard rig of the Rock Giant who “Lit Your Fire” in the 1960’s. The Popular British Combo Organ of the 60’s on the UPPER manual, and an accurate sample of the E. Piano “Rho” Bass on the LOWER Manual.

6. STE GRAND PIANO

The sound of one of the most popular and widely used Acoustic Grand Pianos.

7. TINE PIANO

The sound of the “Rho” Electric Piano, which used “tines” to produce its sound.

8. REED PIANO

The sound of the “Wurl” Electric Piano which used metal “reeds” to produce its sound.

9. CLAV (BD)

The sound of the German Electro-mechanical Stringed Keyboard made popular in “Funky” Music. In this case, the virtual control panel setting of the two tone switches is “BD” as on the original instrument.

10. CHURCH PIPE ORGAN

The sound of a Church Pipe Organ with “Full Organ” registration.